

MEGAMAN® TEGO 2

Table 1 (page 1-2): TEGO 2


Key

Seamless dimming without flicker point and dimming level to 100% to 10%


Moderate dimming and dimming level to 100% to 20%

Dimmer not recommended or not tested

MEGAMAN® TEGO 2

Manufacturer	Model No.	Voltage (V)	Wattage (W)	FDS72300v0-dm/db/sc
				
Busch Jaeger	6523 U-102	230	2-100(LED)	1 to 2
Gira	540100	230	3-100 (Leading) 3-200 (Trailing)	1 to 10
Jung	224LEDUDD	230	3-100	1 to 10
Merten (Schneider)	MEG5134-0000	230	4-40 (Leading) 4-200 (Trailing)	1 to 10
DIMEZE	DZ3G450DIAL	220-240	450	1 to 10
MEGAMAN	SS-LD-150	230V	5-150(LED)	1 to 10
Clas Ohlson	ETM208CO	230	10-100	1 to 10
ADT	ATE-DRT250UK	220-240	3-250(LED)	1
ADT	ATE-LVR100CUK	220-240	2-100(LED)	1
DETA	ATE-VR250	230-240	5-100	1 to 10
Hamilton	H-LEDSTAT	230-240	5-100	1 to 10
Hamilton	LEDITB100	220-240	5-100(LED)	1 to 10

MEGAMAN® TEGO 2

Manufacturer	Model No.	Voltage (V)	Wattage (W)	FDS72300v0-dm/db/sc
				
Varilight	V-Pro MJP300	220/250	0-300(LED)	1 to 10
Varilight	V-Pro Z0JP250/MJP120	220/250	0-120(LED)	1 to 10
Varilight	V-Pro GJE100s	220/250	0-120(LED)	1 to 2
ELKO	EK005107-0D	230	20-315	1 to 10
ABB	6523 U	230	2-100(LED)	1 to 10

Remarks:

The minimum and maximum numbers of LED luminaire compatible depend upon the performance of the dimmer, which is subject to the status of the manufacturer's technology. Due to possible variations in country dimmer module specifications, please contact your local distributor for a list of compatible dimmers before installation. Copyright © MEGAMAN® 2020. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice.
All other trademarks mentioned are the property of their respective owners.